

# 134.2khz FDX-B Pet RFID Reader Writer



**Model No.: QSM5200**

## Summary

QSM5200 is a low frequency tag reader that using wireless identification technology and it supports reading FDX-B(ISO11784/85) tag, it uses high brightness OLED display screen, and can be seen clearly inside the house or under the strong light outside. It can store up to 20000 tag information with its built-in memory, users can send the information to the computer through USB cable or wireless connection to manage data.

## Features

- Ergonomic design, comfortable and convenient;
- Comply with ISO11784/85 standards;
- Support FDX-B;
- Support EMID format like EM4100, TK4100;
- Read fast, easy to operate, free PC communication software.
- Application for Poultry management and Livestock and pets management etc.

## Specifications

Product name:	134.2khz FDX-B Pet RFID Reader Writer
Model	QSM5200
Device Size	28cm*14.7cm*6cm
Tag format:	FDX-B (ISO11784/11785)
Read & write distance:	2*12mm Glass Tube Tag>15cm;30mm Animal Ear Tag>25cm
Reading access time:	<100ms
Signal indicator:	128*64 high brightness OLED, hummer
Power consumption:	Working:0.9W standby : 0.3W
Storage capacity:	6000 items (tag code & time)
Storage time:	> 20 years
Communication interface:	USB2.0,wireless HID(optional ),Bluetooth (Optional )
Weight:	300g (without batteries)
Operating temperature:	-10°C~50 °C
Storage temperature:	-30 °C~70 °C

**Packing:**



Address: Floor 1012, Jinhua building, Long Feng 3 Road, Longhua New District, Shenzhen  
Tel: 0755-23760901, Fax: 0755-23716537,

Web: [www.rfid-global.com.cn](http://www.rfid-global.com.cn),

Email: [sales@rfid-global.com.cn](mailto:sales@rfid-global.com.cn)